

NSP-1400T

Dual-Switch Dual-Light™ Flashlight- Non-Rechargeable

MARKET APPLICATIONS

Law enforcement, fire & rescue, industrial, security, hardware/tool, automotive, hunting/recreation.

DESCRIPTION

This non-rechargeable dual-switch Dual-Light™ flashlight has two body switches offering the user a choice of flashlight, floodlight or dual-light operation. Its compact oval design makes it convenient to use and carry. The water resistant housings are made from engineered polymer and have a soft touch finish. The light a white flashlight and a white floodlight and comes with a removable pocket/belt clip. Power comes from 2 included AAA batteries.

CASE MATERIAL

Engineered Polymer - Tan

DIMENSIONS

Length: 5.3 inches (135 mm) • Handle diameter: 1.1 x 0.8 inches (28 x 20 mm)

WEIGHT

Weight: 2.2 oz. (62 g) with batteries installed.

LENS

Unbreakable polycarbonate with scratch resistant coating.

LIGHT SOURCE

Cree® LED. Impervious to shock with a 50,000 hour lifetime.

LIGHT OUTPUT

Flashlight - 60 lumens, Floodlight - 25 lumens, Dual-Light - 90 lumens

ON/OFF

Top Body Switch - Flashlight, Bottom Body Switch - Floodlight, Both - Dual-Light

RUN-TIME

Flashlight - 3 hours, Floodlight - 3 hours, Dual-Light - 1.5 hours

BATTERY

2 AAA Premium Batteries (included)

FEATURES

- CREE® LED technology – 50,000+ hours LED
- Flashlight/Floodlight/Dual-Light™
- Focused flashlight beam for distance illumination
- Unfocused wide-beam floodlight for close-up illumination
- Dual-Light (flashlight and floodlight on at the same time) for maximum versatility
- Engineered polymer housing with Soft-touch finish
- Dual body switches
- Non-slip grip
- Water resistant
- Impact & chemical resistant polymer housing
- Powered by 2 AAA premium batteries (included)

WARRANTY

*Limited 1 Year Warranty - Product is warranted to be free from defects in workmanship and materials to the original purchaser for one (1) year from the date of purchase, and includes the LEDs, housing, lenses, electronics, switches, rechargeable batteries and chargers. Disposable non-rechargeable batteries are excluded from this warranty. Normal wear and failures which are caused by accidents, misuse, abuse, faulty installation and lightning damage are also excluded.

APPROVALS

